

|             |                       |   |
|-------------|-----------------------|---|
| System      | CPU                   | RK3566 Quad-core Cortex-A35   |
|             | RAM                   | 2GB   |
|             | Internal memory       | 16 GB   |
|             | Operation system      | Android 11  |
|             | Touch screen          | 10-Point capacitive touch of 3mm thickness glass and 15mm outer frame |
| Display     | Panel                 | 10.1" LCD IPS panel   |
|             | Resolution            | 1280x800  |
|             | Contrast ratio        | 700   |
|             | Luminance             | 400cdm2   |
|             | Aspect Ratio          | ,16:9   |
| Network     | WiFi                  | 802.11b/g/n   |
|             | 3G dongle             | 3G USB dongle ext.  |
|             | Ethernet              | RJ45 / POE  |
|             | Buletooth             | BT4.0   |
| Interface   | Card slot             | SD,Support up to 32GB   |
|             | USB Device            | USB x2  |
|             | HD-MI                 | HD-MI Input   |
|             | Power Jack            | DC power input  |
|             | RJ45                  | YES   |
|             | Earphone              | 3.5mm earphone  |
| Media plays | Video format          | MPEG-1,MPEG-2,MPEG-4,H.263,H.264,VC1,RV etc.,support up to 1080p      |
|             | Audio format          | MP3/WMA/AAC etc.  |
|             | Photo                 | jpeg  |
| Other       | Wall mounting bracket | 75*75mm VESA  |
|             | Speaker               | 2*2W  |
|             | Camera                | 2.0M/P  |
|             | Language              | Multi-language  |
|             | Application           | MSN/Skype/Facebook/Twitter/Youtube/E-mail/google map etc              |
|             | Color                 | Black   |
| Accessories | Adapter               | Adapter,12V/2A  |
|             | User manual           | No  |